

Instruction Manual

Under Tailgate Spreaders Electric 12 VDC 92440SSA

Table of Contents


Warranty Information	1
Spreader Installation Instructions	1,2
Spreader Installation Drawing	2
Spinner Assembly Instructions	3,4
Spinner Assembly Drawing	3,4
Operating Instructions	5,6
Recommended Maintenance	6
Parts list	7
Parts List: Hardware Box	8
Spinner Components Drawing	8

UNDER TAILGATE SPREADER WARRANTY

This warranty replaces all previous warranties and no employee of this company is authorized to extend any additional warranties, or agreements, or implications not explicitly covered herein. Buyers Products Company warrants all parts of the product to be free from defects in material and workmanship for a period of (1) one year from the date of original installation. Parts must be properly installed and used under normal conditions. Normal wear is excluded.

Any part which has been altered, including modification, misuse, accident, or lack of maintenance will not be considered under this warranty. The sole responsibility of Buyers Products Company under this warranty is limited to repairing or replacing any part(s) which are returned, prepaid, 30 days after such defect is discovered, and returned part(s) are found to be defective by Buyers Products Company.

Authorization from Buyers Products Company must be obtained before returning any part. The following information must accompany defective parts returned to Buyers Products Company: RMA#, spreader model, serial number, date installed, and distributor from whom it was purchased. Buyers Products Company shall not be liable for damage arising out of failure of any unit to operate properly, or failure, or delay in work, or for any consequential damages. No charges for transportation or labor performed on any part will be allowed under this warranty.



Installation Instructions


NOTE: The left and right end plates may, on occasion, get bent through improper handling during shipment or storage. If this should happen, square and true the left and right end plates before installation.

1. Aligning the spreader:

- **A.** Position the spreader with the truck such that the auger gear motor is located on the right side of the truck (passenger side).
- **B.** Lift the spreader up and under the dump body tailgate, positioning the spreader forward as close as possible to the dump body. The tailgate of the dump body should lay down horizontally over the spreader.
- **C.** Support the spreader solidly and securely when positioning for mounting.
- **2.** Attach mounting brackets: (See Fig. 1.)
- **A.** Attach a quick detach plate, (1) to both sides of the spreader frame using hinge pins (2) and a hairpin cotter pins (5).
- **B.** Position the (2) quick detach plates over the dump body rub rails and flush with rear edge of dump body.
- **C.** Weld the quick detach plates to the dump body rub rails. Weld the plates continuously around 3 sides of each plate. Do not weld along the edge of the plates next to the attachment pin.



Mounting Hardware Installation Drawing




ITEM	QTY.	DESCRIPTION	
1	2	Quick Detach Plate	3009526
2	2	Hinge Pin	3011139
3	2	Hanger Iron Brace	3011137
4	2	Pin Brace	3000210
5	6	Hair Pin Cotter 5/32"	HP12

- **D.** Align the pin brace (4) on the dump body using the iron brace (3) for exact positioning. For proper fit, hanger iron brace may require some minor bending.
- **E.** Weld the pin braces (4) to the dump body sides, all around
- **F.** Attach the iron braces (3) to the pin braces on the sides of the dump body and the sides of the spreader using two hairpin cotter pins (Item 5).
- **G.** If there is a gap between the spreader and the dump body, weld or bolt a steel strip to the forward edge of the spreader to cover the gap.
- **H.** If you have purchased the tailgate side shields (purchased separately as P/N 924F0106), bolt or weld them to the inside of the tailgate to prevent material spillage at the ends of the spreader.



2. Spinner assembly installation:


Figure 2



- **A.** Attach heights adjustment bracket (1) to spreader lower tray using rod hinge (2) and hair pins.
- **B.** Attach spinner motor assembly (3) to heights adjustment bracket (1) using $\frac{1}{2}$ -13 screws and nuts.
- **C.** If extra clearance required, use upper holes in heights adjustment bracket.
- **D.** Attach spinner shield (7) to heights adjustment bracket (1) using 5/16-18 screws and nuts.
- **E.** Attach spinner disk (4) to motor shaft using clevis pin and cotter pin.

ITEM	QTY.	DESCRIPTION	
1	1	Bracket Heights Adj. Weldment	3017175
2	1	Rod, Hinge	3006646
3	1	Bracket Spinner Motor Assembly	3017176
4	1	Spinner, 14" Poly CCW	3016394
5	1	Pin, Clevis, 5/16 x 2-1/2, .141 Hole ZN	V 3007113
6	1	Cotter Pin, 1/8 x 1, Zinc	FPC013000100
7	1	Shield Spinner Disk	3017172
8	4	Pin, Hair Cotter 5/32" ZN 3.25 OAL	HP12
9	2	Screw, HHC 1/2-13x1.50 SST	FCS050013150SS
10	2	Nut, Nylock 1/2-13 Zinc	FNE050013053SS
11	3	Screw, Hex HD, 5/16-18 x 3/4 GR5 S	S 3006721
12	3	Nut, Hex Flange - 5/16-18 SS	3006719
13	2	Weldment, Parallel Linkage	924F0012
14	2	Washer, Flat 1/2 ID SST	3003873
15	1	Angle, Spinner Lug	3006645








Figure 4

- **F.** The leveling mechanism may now be mounted. Park truck on flat, level surface. With spinner assembly in level position, carefully measure "L" and "D" distances. Use any of 3 available holes in heights adjustment bracket. Locate angle (15) such that ½" hole will position with D1=D and L1=L. Modify angle if necessary.
- **G.** Secure angle (15) to the truck frame.
- **H.** Attach parallel linkage rods (13) to heights adjustment bracket and angle. Secure them using ½" washers and hair pins.
- I. Clamp parallel linkage rods together. To verify leveling action, slowly raise the dump. Be sure that spinner motor assembly and linkages do not have any interference with truck body and it does not have contact with the road. After checking weld parallel linkage bars together.

- **J.** Keeping the spinner assembly level, secure the spinner frame in place using the set screw or 5/16-18 hex screw.
- 3. Control Box and Vehicle Wiring Harness Installation

MAKE SURE YOU HAVE CONNECTED THE PROPER WIRE COLOR.

THIS IS WIRE GROUND ELECTRICAL SYSTEM! NO CONNECTIONS TO TRUCK'S FRAME OR BODY ALLOWED!

WARNING

WARNING! Do not drill holes into fuel tanks, fuel lines, through electrical wiring, etc that may be damaged by drilling. To insure good performance of your spreader, check the condition of truck's electrical system. Using digital voltmeter, check alternator and battery voltage. With engine running and head lights and heater fan ON good voltage reading should fall between 13.0 and 15.3 volts. If voltage reading falls out of this range, check and adjust your electric system.

NOTE: Always disconnect battery before attempting to install electrical components on your vehicle.


A. Mount the controller in a convenient location in the truck cab. It is recommended not to mount the controller directly in front of heat vents. Allow ample air space around controller.

A CAUTION

DO NOT MOUNT CONTROLLER IN THE WAY OF AIR BAG DEPLOYMENT!

- **B.** Route both wire harnesses into truck cab through firewall (it maybe necessary to drill holes). Insulate hole to avoid water leaks.
- **C.** Insure no wires are nicked or damaged during installation.
- **D.** Connect the 4-pin connector on the wire harness to the control box 4-pin connector.
- **E.** Connect the 2-pin connector on the power cable to the control box mating connector.
- **F.** Connect wire harness single connectors to control box connectors.
- **G.** Connect fuse connector to the fuse terminal or ignition switch (5 AMP max).
- **H.** Lay out a path for the power cable to the battery, use quick ties to secure power cable.
- DO NOT CONNECT TO BATTERY AT THIS TIME!
- I. Lay out path for wire harness to the rear of the vehicle. It is recommended to stay clear of the exhaust system. Excess heat can damage the wire harnesses. Use quick ties to secure harness to underbody.
- J. Connect the wire harness to the motor. Make sure wire colors on wire harness match colors on the motor.





Thoroughly clean battery terminals. Make sure battery terminals have no tarnish or corrosion. DO NOT CONNECT WIRE HARNESS TO DAMAGED OR CORRODED TERMINALS!

IT MAY RESULT IN OVERHEATING, LOST POWER AND POTENTIAL CONTROLLER DAMAGE!

- **K.** Connect the power cable directly to the battery.
- **L.** Insure all functions of the controller are working properly.
- **M.** Observe auger moving in proper direction. If direction is wrong reverse wires between Motor and Wire Harness.
- ${f N}.$ Optional spot light (5 AMP max) can be installed on spreader. Remove cap from single white wire. Connect light to this wire and trucks frame.

A IMPORTANT

IMPORTANT Make sure all wires securely attached to vehicle or spreader. Use wire ties and/or wire clamps to attach wires. All excess wires must be rolled into bungles and attached to vehicle or spreader.





Figure 5



Spreader Assembly Parts List




ITEM	QTY.	DESCRIPTION	PART NO.	
1	1	Frame, Welded, 96 UTS SS	3015029	
2	1	Tray, Lower Weldment, SS 96 UTS	3015033	
3	2	Latch, Cover HNG MTG BRKT	3008447	
4	1	Rod, Latch, UTS Tray SST PS	3015031	
5	1	Rod, Latch, UTS Tray SST DS	3015030	
6	1	Gasket, Felt Bearing	9240087	
7	1	Bearing, 1-1/4 Flange 2 Hole	9240086	
8	1	Adapter, Gear Motor, Weldment	3014455	
9	1	Bearing, Flanged 1-1/8"	1410200	
10	2	Screw, HCAP 7/16-14 x 1.25 SST	3014755	
11	2	Nut HEX NYLOCK 7/16-14 SST	3014756	
12	3	Washer, Flat 1/2 USS, SST	3000269	
13	3	Screw, HHC- 1/2-13 X 1 SST	FCS050013100SS	
14	1	Gear Motor Conveyor 12 VDC	3013821	
15	12	Washer, Flat 3/8 USS SST	FWF038100007SS	
16	15	Screw, HHC 3/8-16 x 1 304 SST	FCS038013100SS	
17	1	Weldment, 96 UTS Auger	924F0081	
18	1	Sleeve, Auger Adapter	3014858	
19	1	Screw, HHC - 1/2-13 x 3 SST	3001250	
20	1	Nut, Nylock 1/2-13 Zinc	FNE050013053SS	
21	11	Nut, Nylock 3/8-16 SST	FNE038016044SS	
22	6	Nut, Hex FLNG 3/8-16 SST	3001255	


ITEM	QTY.	DESCRIPTION	PART NO.
23	1	Plate, Spinner Cover	3000270
24	2	Nut NYLOCK 5/8-11 SST	3001247
25	2	Screw, HHC - 3/8-16 X 3.5 SST	3001249
26	5	Pin, Hair Cotter, Clear Zinc	1420016
27	1	Decal, #1, Danger Stay Clear	9240131
28	2	Screw, HHC - 3/8-16 X 1.25 SST	FCS038016125SS
29	1	Plate, Auger Cover	3014897
30	4	Pin, Clevis 3/8 x 1.125 SST	BCP84620SS
31	1	Weldment, Cover, 96IN UTS SST	3012956
32	2	Bracket, SST Cover Latch w. Holes	3006968
33	2	Handle, Stainless Steel Locking	3000268
34	1	Decal, Salt Dogg, BLK/WHT on CLR	3011132
35	1	Cover, Gear Motor Weldment	3017187
36	2	Screw, HHC - 5/16-18 X 5/8 SST	FCS031018063SS
37	1	Cover Side Gear Motor	3017186
38	2	Bracket, Receptacle SZ8 Deutsch	3017121
39	2	Screw, HHC - 3/8-16 X 1.25 SST	3006760
40	1	Plug 1.00' Dome Heyco 1702	3017483
41	2	Bushing Strain Relief Heyco 2047	3017482
42	3	Screw #12-14x. 74 SS	3015873
43	1	Decal #2, Danger Before Svce	9240132



Hardware Box Parts List



Hardware Bag Contents



(DE)

Bill of Materials

ITEM	QTY.	DESCRIPTION	PART NO.
1	2	Pin, SS Brace	3000210
2	4	Screw, HEX HD, 5/16-18 x 3/4 GR5 SS	3006721
3	10	Pin, Hair Cotter 5/32" ZN 3.25 OAL	HP12
4	10	Nut, HEX Flange - 5/16-18 SS	3006719
5	3	Washer, Flat 1/2 ID SST	3003873
6	2	Pin, Clevis, 5/16 x 2-1/2, .141 Hole ZN	3007113
7	1	Cotter Pin, 1/8 x 1, Zinc	FPC013000100
8	1	Strap Hose, .625 ID, 25 PCS/BAG	HK1113
9	1	Nut, Wing 3/8-16 Zinc Cold Forged	3005723
10	2	Screw, HHC-1/2-13 x 1.50 SST	FCS050013150SS
11	2	Nut, Nylock 1/2-13 Zinc	FNE050013053SS

Spinner Shield Disk

Angle, Spinner Lug

Wire Harness, Main

Wire Assembly, 36 Long

Pin, Hinge, SST

Power Cord

Rod, Hinge

Spinner, 14" Poly CW

Weldment, Parallel Linkage

Bracket, Hanger, UTS SST

Plate, Detach, Mount SST

Hardware Bag, UTS Electro

Controller Speed 12 VDC, 60 AMP

Bracket Heights Adj. Weldment

Instruction Manual, UTS Electro

1

1

1

2

2

5

6

7

8

PART NO.

3017176

3017172

3016394

924F0012

3006646

3006645

3011137

3009526

3011139

3015181

3016934

3016944

3016943


0203700

3017175

3017501



Spreader Motor Assembly



ITEM	QTY.	DESCRIPTION	PART NO.
1	1	Bracket Weldment, Spinner Moto	or 3017171
2	1	Motor 12 VDC, .5 HP Spinner	3016309
3	4	Screw, HHC 3/8-16 x 1 304 SST	FCS038016100SS
4	1	Cover, Motor, Drilled	3017174
5	3	Screw, Cap 1/4-20 x 3/4 SST	FCS025020075SS
6	1	Wire Harness, Chute	3006753